

Product data sheet

Specifications



APC Replacement Battery Cartridge, VRLA battery, 11Ah, 12VDC, 2-year warranty

RBC6

Product availability : Stock - Normally stocked in distribution facility

Overview

Lead time	Usually in Stock
-----------	------------------

Main

Product or Component Type	Replacement battery cartridge
Number of cables	1
Battery Type	Lead-Acid battery
Provided Equipment	All required connectors Battery recycling guide Reusable packaging Installation guide

Batteries & Runtime

Battery Slots Empty	0
Included Battery Modules	0
RBC Quantity	1

Replacement battery

Physical

Color	Black
Height	3.70 in (9.4 cm)
Width	5.98 in (15.2 cm)
Depth	7.72 in (19.6 cm)

Net Weight	16.93 lb(US) (7.68 kg)
Mounting Mode	Not rack-mountable
USB compatible	No

Environmental

Ambient air temperature for operation	32...104 °F (0...40 °C)
Operating altitude	0...10000 ft
Relative Humidity	0...95 %
Ambient Air Temperature for Storage	5...113 °F (-15...45 °C)
Storage altitude	0...50000 ft (0.00...15240.00 m)
Storage Relative Humidity	0...95 %

Ordering and shipping details

Category	11309-APC RESALE PRODUCTS
Discount Schedule	APC1
GTIN	731304003281
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.89 in (17.5 cm)
Package 1 Width	10.20 in (25.9 cm)
Package 1 Length	11.89 in (30.2 cm)
Package 1 Weight	18.63 lb(US) (8.45 kg)

Offer Sustainability

Sustainable offer status	Green Premium product
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
REACH Regulation	REACH Declaration
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End of Life Information
Take-back	Take-back program available

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Recommended replacement(s)